

Bảng thông số sản phẩm

Đặc điểm

51213

Varlogic PF Controller RT12 step 440V



Main

Range	VarPlus
Range of product	Varlogic
Product name	VarLogic RT
Device short name	RT12
Product or component type	Power factor controller

Complementary

Number of step output contacts	12
[Us] rated supply voltage	320...460 V AC 50/60 Hz
Measurement current	50 mA
Operating mode	Manual
Display type	7 segments LED 4-digit
Type of measurement	Power factor
Alarm function	5 last alarms
Input type	Phase to phase Current input CT...10000/5 A
Output type	Free outputs contacts current: 0.3 A 110 V DC Free outputs contacts current: 0.6 A 60 V DC Free outputs contacts current: 1 A 400 V AC 50/60 Hz Free outputs contacts current: 2 A 24 V DC Free outputs contacts current: 2 A 250 V AC 50/60 Hz Free outputs contacts current: 5 A 120 V AC 50/60 Hz
Type of setting	Target cos phi: 0.85 inductive...1
Measurement accuracy	+/- 2 %
Time delay range	10...1800 s 10...1800 s (on reconnection)
Step sequences	1.1.2.4 1.2.2.2 1.2.4.8 1.1.2.2 1.1.2.3 1.2.3.3 1.2.3.4 1.2.4.4

Miễn trừ trách nhiệm: Tài liệu này không nhằm thay thế và không được sử dụng để xác định tính phù hợp hoặc độ tin cậy của các sản phẩm này cho các ứng dụng người dùng cụ thể

1.1.1.1
Linear
1.2.3.6

Mounting location	In cabinet Panel
Height	143 mm
Width	143 mm
Depth	67 mm
Net weight	0.8 kg

Environment

Standards	EN 61010-1 IEC 61326 IEC 61000-6-2 IEC 61000-6-4
IP degree of protection	Rear face: IP20 Front face: IP41 conforming to IEC 60429
Ambient air temperature for operation	0...55 °C

Packing Units

Package 1 Weight	1.127 kg
Package 1 Height	0.850 dm
Package 1 width	1.870 dm
Package 1 Length	2.300 dm

Offer Sustainability

EU RoHS Directive	Compliant EU RoHS Declaration
China RoHS Regulation	China RoHS declaration Product out of China RoHS scope. Substance declaration for your information
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Contractual warranty

Warranty	18 months
----------	-----------